
## In-Ceiling Mounting Bracket Kit

## V2000D-IC

## For Indoor Dome Camera

# **Quick Guide**

#### 1. Product Overview






FIGURE 1-1: PHYSICAL DIMENSIONS

### 2. Installation and Mounting

## **Package Content**

Check that all the items listed below are included in the packing box.

- Ceiling Mount \* 1
- Ceiling Plate \* 1
- M4x8-BK Screws \* 2
- Mounting Template \* 1
- Printed Quick Guide \* 1

### **Required Tools**

The following tools might be helpful for completing the installation.

- Phillips Head Screwdriver \* 1
- Ceiling Cutting Tool \* 1
- Wire Cutters


## Installation & Mounting Procedure

 Use the mounting template included to cut a 7.8 in. (198 mm) hole in the ceiling.



FIGURE 2-1: MOUNTING TEMPLATE

2. Insert the ceiling mount bracket into the hole.







FIGURE 2-2: INSERT THE CEILING MOUNT

 Using a Philips screwdriver, turn the 2 bracket screws to extend the locking arms. Tighten the screws to compress the locking arms to the ceiling.



Using the screws provided, fasten the camera onto the inceiling mount. Position the camera. Install the camera cover onto the camera.




FIGURE 2-4: CAMERA INSTALLATION

Note that the screw holes highlighted in red (below) are the exact locations for securing the screws with the camera body.




FIGURE 2-5: CEILING MOUNT INTERNAL

 Attach the 2 spring hooks from the ceiling plate to the mounting tabs of the ceiling mount and evenly push the ceiling plate upward until it clicks into place




FIGURE 2-6: ASSEMBLE THE CEILING PLATE

6. The in-ceiling installation is complete, as the following figure




FIGURE 2-7: MOUNTING COMPLETION

The figure below illustrates the internal view of completed mounting of indoor camera and in-ceiling mounting bracket kit




FIGURE 2-8: MOUNTING COMPLETE - INSIDE VIEW

### Notes & Warnings

- The hole for the in-ceiling mount has a diameter of 7.8 in./198 mm. Make sure the cutout hole is of correct size for proper fit.
- When drilling the hole, make sure the ceiling thickness is no more than 1.4 in. (35 mm) to maintain its structural integrity.
- Make sure there are no damaged parts prior to assembly.

# 3. Specification

Material	PC + ABS
Color	White
Dimensions	Ceiling Mount: 2.5 x 9.9 x 2.4 in. (63 x 250.5 x 60.5 mm)
	Ceiling Plate: inner - Φ3.8 in. (96.4 mm), outer - Φ 8.7 in. (222 mm)
Weight	0.9 lb (400 g)

Product specifications subject to change without notice. Vicon part number: 8009-8318-91-00 8/2024 Copyright ©2024 Vicon Industries Inc. All rights reserved.